

**Features:**

- High power 670 nm band SM fiber-coupled SLD modules
- Bell-shaped spectrum
- FC/APC connectors
- 

**Applications:**

- Optical sensors
- Optical coherence tomography
- Optical measurements
- Atomic force microscopy
- Others

**Custom:**

- DIL and other packages
- **655 nm** center wavelength upon request

**Specifications (Nominal Emitter Stabilization Temperature +25 °C)**

Parameter		Min	Typ	Max
Output power, $P_{op}$ , ex SM fiber, mW	HP1	4	—	5
	HP2	8	—	10
Forward current at $P_{op}$ , mA	All	—	150	220
Forward voltage at $P_{op}$ , V	All	—	2.6	3.0
Central wavelength at $P_{op}$ , nm	All	660	670	680
Spectrum width at $P_{op}$ , FWHM, nm	All	6.0	7.5	—
Residual spectral modulation depth <sup>†</sup> at $P_{op}$ , %	All	—	1.0	2.0
Secondary coherence subpeaks at $P_{op}$ , dB (10 log)	All	—	<-20	—
Slow / fast polarization ratio (PM modules) at $P_{op}$ , dB	All	7.5	10	—
Operating temperature at $P_{op}$ , °C	All	-55	—	+75
Storage temperature at $P_{op}$ , °C	All	-55	—	+85
PD monitor current at 20 mW power, μA	All	100	—	—
PD monitor bias voltage, V	All	—	—	5.0
Cooler current, A	All	—	—	1.2
Cooler current, V	All	—	—	3.5
Thermistor BETA, K	All	—	3892	—
Thermistor Resistance at 25 °C, kΩ	All	—	10	—

**Attention** – typical parameters are not guaranteed. Contact Superlum representative if you require a tighter tolerance of spectral parameters

<sup>†</sup> Rated at maximum power, typically decreases linearly with power





Output power must never exceed  $P_{Max}$ .

The following part numbers should be used when **ordering**:

SLD-261-(a)-(b)-(c)-PD-670,  
 where: (a) – power category (HP1 or HP2),  
 (b) – package type (DBUT – standard),  
 (c) – type of fiber—SM (isotropic) or PM (polarization maintaining),  
 PD – monitor photodiode, FC/APC – connector type.

Example: SLD-261-HP2-DBUT-SM-PD-670-FC/APC

## TYPICAL PERFORMANCE EXAMPLES



Mirror displacement = Optical path difference / 2

Examples demonstrate typical performance only.  
Actual performance may vary from sample to sample and from lot to lot.

All specifications are subject to change without notice.