

Description

Mi-Wave's 525 series Dial Type Uncalibrated Phase Shifter

Notes

S/N: N/A

Electrical Specifications

	Minimal	Typical	Maximum
Frequency Range	90 GHz		140 GHz
Phase Shift		0-180 Degrees	
Insertion Loss		0.6 dB	
Average Power			0.3 Watts
VSWR		1.25:1	

Physical Specifications

Input and Output Ports	WR-08 Waveguide
Flanges	UG-387/U-M
Housing Material and Finish	Black Anodized Aluminum
Waveguide Material and Finish	Gold Plated Aluminum

Tested by: Kim Madden

Date: 2021-04-05